



RETEKES

TD015 User Manual





Henan Eshow Electronic Commerce Co., Ltd
Add: 7/F, Sanjiang Building, No.170 Nanyang Road, Huji District, Zhengzhou, Henan, China
EU Importer:Germany Retevis Technology GmbH
Address:Uetzenacker 29,38176wendeburg
Facebook: facebook.com/Retekess.ru
E-mail: support@retekess.com.ru
Web: retekess.com.ru



MADE IN CHINA

Product List

- Receiver Case *1
Receiver Case Power *1 (5V/2A)
Remote Control *1
Keypad*1
Keypad Power*1 (9V/1A)
HDMI Cable *1
Antenna Cable *1



Wireless Calling System-User Manual


1. Program Settings

Table with Base Setting, Code Setting, Ballot Screen, Custom Setting, Volume Setting, Enter the boot page, System Setting, current Version:4.6.5, www.retekess.com

Press the MENU button on the remote control to enter the program setting mode

2. Code Setting


- Pairing: Press the MENU button on the remote control to enter the program setting mode
Keypad ID: Enter the number on the keyboard that you want to pair, then press CALL to confirm.
Window name: It could be set by entering any of the LETTERS on the keyboard
After entering the LETTERS, using remote control to click SAVE on the screen to complete the pairing setting.



Deleting: If you need to delete any paired ID, using the remote control to select the corresponding ID and click OK button, there will


ad.txt: Subtitle File that scrolls subtitles at the bottom of the display.
logo.png: Merchant LOGO (the merchant LOGO is shown in the upper left corner of the main interface, you could replace the original file with your own LOGO. It is PNG format, the ratio of width to height is recommended to be 5: 1 and do not use the LOGO in black color.)
NOTE:
Do not change the file names are listed in red. Otherwise, the system cannot recognize them normally. Please follow the naming convention when creating or replacing these files.
You can customize video, music, MV and picture's name. The system does not support the video in MKV and FLV format.
All files must be placed in the "TM100" folder, and put the "TM100" folder in the root directory of the removable disk.
If both "logo.png" and "logo.jpg" files are included, the system will display "logo.png" by default.

6. Volume Setting




- Call volume setting: Select the Prompt Volume Setting option, click OK button to enter the setting mode, set the volume up down by pressing the Forward and Backward buttons. Click Exit to return after selecting.
Video volume setting: Select the Video Volume Setting option, click OK button to enter the setting mode, set the volume up down by pressing the Forward and Backward buttons. Click Exit to return after selecting.

7. System Setting



- Display: Screen Zoom, freely select the screen to zoom in or out to adjust the program window size, Default set is never turn off the display.
Applications: Using the "Auto Clear" function in "Basic Settings" to clear call information
Storage and Factory Reset: All applications in the system will be deleted if the system is reset to factory settings.
Language



CE Requirements:
(Simple EU declaration of conformity) Henan Eshow Electronic Commerce Co.,Ltd declares that the radio equipment type is in compliance with the essential requirements and other relevant provisions of RED Directive 2014/53/EU and the RoHS Directive 2011/65/EU and the WEEE Directive 2012/19/EU, the full text of the EU declaration of conformity is available at the following internet address: www.retekess.com.
Disposal
The crossed-out wheeled-bin symbol on your product, literature, or packaging reminds you that in the European Union, all electrical and electronic products, batteries, and accumulators (rechargeable batteries) must be taken to designated collection locations at the end of their working life. Do not dispose of these products as unsorted municipal waste. Dispose of them according to the laws in your area.

IC Requirements:
Licence-exempt radio apparatus This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:
This device may not cause interference.
This device must accept any interference, including interference that may cause undesired operation of the device. Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

RF Exposure Information
DO NOT operate the radio without a proper antenna attached, as this may damage the radio and may also cause you to exceed RF exposure limits. A proper antenna is the antenna supplied with this radio by the manufacturer or an antenna specifically authorized by the manufacturer for use with this radio, and the antenna gain shall not exceed the specified gain by the manufacturer declared.
DO NOT transmit for more than 50% of total radio use time, more than 50% of the time can cause RF exposure compliance requirements to be exceeded.
During transmissions, your radio generates RF energy that can possibly cause interference with other devices or systems. To avoid such interference, turn off the radio in areas where signs are posted to do so.
The device complies with RF specifications when the device used at 5mm from your body. Third-party belt-clips, holsters, and similar accessories used by this device should not contain any metallic components. Body-worn accessories that do not meet these requirements may not comply with RF exposure requirements and should be avoided.
DO NOT operate the transmitter in areas that are sensitive to electromagnetic radiation such as hospitals, aircraft, and blasting sites.

Avoid Choking Hazard

Small Parts. Not for children under 3 years.

Protect your hearing

- Use the lowest volume necessary to do your job.
Turn up the volume only if you are in noisy surroundings.
Turn down the volume before adding headset or earpiece.
Limit the amount of time you use headsets or earpieces at high volume.
When using the radio without a headset or earpiece, do not place the radio's speaker directly against your ear
Use careful with the earphone maybe possible excessive sound pressure from earphones and headphones can cause hearing loss Note: Exposure to loud noises from any source for extended periods of time may temporarily or permanently affect your hearing. The louder the radio's volume, the less time is required before your hearing could be affected. Hearing damage from loud noise is sometimes undetectable at first and can have a cumulative effect.

Avoid Burns

- Antennas
Do not use any portable radio that has a damaged antenna. If a damaged antenna comes into contact with the skin when the radio is in use, a minor burn can result.
Batteries (if appropriate)
When the conductive material such as jewelry, keys or chains touch exposed terminals of the batteries, may complete an electrical circuit (short circuit the battery) and become hot to cause body injury such as burns.
Exercise care in handling any battery, particularly when placing it inside a pocket, purse or other container with metal objects
Long transmission
When the transceiver is used for long transmissions, the radiator and chassis will become hot.

Safety Operation

be pop up the "Confirm Deletion?" on the screen, then press OK to confirm.

Note: If you need more than one keyboard transmitters work together with the system, you need to pair the keyboard transmitter one by one instead of pairing them at the same time. Also you need to make sure the keyboard ID number displayed on the screen is the one keyboard that you are pairing currently.

3. Internet Setting

Press the MENU button on the remote control to enter the System Setting mode, and select the Internet.




3.1.1 WLAN

- Select the WLAN to refresh the available Network list
Select the Network that you need to join, press OK button on the remote control, then enter the correct password of the Network and select Join to be done.

3.1.2 Wired Network

- Connect one end of the network cable to the Ethernet interface of the box
Select Wired Network option, the system will obtain the IP and then connect to the Network automatically.


4. Basic Setting



- Model: Select the scene mode that comes with the system. If you need to customize it, please refer to "Custom Ads".
Auto clear: The time to auto clear the call information on the display.
Loop display: The time of the call information cycle display
Advertisement: Videos or images switching interval time
Switch times: The time set for the calling interface to switch back to the main interface
Speak times: Repeat prompt times for one call

5. Custom Settings

5.1 Custom statement



- Select the Text Box to enter Edit Mode
Enter the scene description that you need. The Call Number and Window Name must be replaced by three capital letters "XXX". e.g. XXX please go to XXX take the meal
Select "Save" option after input
Enter the "Basic Settings" and select the custom scene mode in "Mode Selection".

5.2 Custom Ads



The default language is English, available in multiple languages

7.5 Security and restrictions

The system unknown source option is turned on, you can install programs and program upgrade packages



8.6 System Update

- Insert U-disk--Press MENU button to enter Program Setting--Select System Setting--Device (Application)--System Application (File manager)--Mobile Storage--Press OK to enter the document list.
Select a program APP with an extension ending in ".APK", click OK to install.
Select the "Install" option to confirm the upgrade. The program will automatically restart after the upgrade. Do not remove the storage device and cut off the power during the upgrade.

RF ENERGY EXPOSURE AND PRODUCT SAFETY GUIDE

Before using this radio, read this guide which contains important operating instructions for safe usage and RF energy awareness and control for compliance with applicable standards and regulations.

This radio uses electromagnetic energy in the radio frequency (RF) spectrum to provide communications between two or more users over a distance. RF energy, which when used improperly, can cause biological damage.
All Reteless radios are designed, manufactured, and tested to ensure they meet government-established RF exposure levels. In addition, many manufacturers also recommend specific operating instructions to users of the radios. These instructions are important because they inform users about RF energy exposure and provide simple procedures on how to control it. Please refer to the following websites for more information on what RF energy exposure is and how to control your exposure to assure compliance with established RF exposure limits: http://www.who.int/en/

Local Government Regulations

When radios are used as a consequence of employment, the Local Government Regulations requires users to be fully aware of and able to control their exposure to meet occupational requirements. Exposure awareness can be facilitated by the use of a product label directing users to specific user awareness information. Your Reteless radio has a RF Exposure Product APP with an extension ending in ".APK", click OK to install.
Select the "Install" option to confirm the upgrade. The program will automatically restart after the upgrade. Do not remove the storage device and cut off the power during the upgrade.

Radio License (if appropriate)

Governments keep the radios in classification, business radios operate on radio frequencies that are regulated by the local radio management departments (FCC,ISED, OFCOM, ANFR, BfTK, Bundesnetzagentur,...) To transmit on these frequencies, you are required to have a license issued by them. The detailed classification and the use of your radios, please contact the local government radio management departments. Use of this radio outside the country where it was intended to be distributed is subject to government regulations and may be prohibited.

Unauthorized modification and adjustment

Changes or modifications not expressly approved by the party responsible for compliance may void the user's authority granted by the local government radio management departments to operate this radio and should not be made. To comply with the corresponding requirements, transmitter adjustments should be made only by or under the supervision of a person certified as technically qualified to perform transmitter maintenance and repairs in the private land mobile and fixed services as certified by an organization representative of the user of those services. Replacement of any transmitter component (crystal, semiconductor, etc.) not authorized by the local government radio management departments equipment authorization for this radio could violate the rules.

FCC Requirements:

- This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
This device may not cause harmful interference, and
This device must accept any interference received, including interference that may cause undesired operation. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
Reorient or relocate the receiving antenna.
Increase the separation between the equipment and receiver.
Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
Consult the dealer or an experienced radio/TV technician for help.

WARNING
Do not use charger outdoors or in moist environments, use only in dry locations/conditions.
Do not disassemble the charger, that may result in risk of electrical shock or fire.
Do not operate the charger if it has been broken or damaged in any way.
Do not place a portable radio in the area over an air bag or in the air bag deployment area. The radio may be propelled with great force and cause serious injury to occupants of the vehicle when the air bag inflates. To reduce risk, pull by the plug rather than the cord when disconnecting the charger.
Unplug the charger from the AC outlet before attempting any maintenance or cleaning.
Contact Reteless for assistance regarding repairs and service.
The adapter shall be installed near the equipment and shall be easily accessible
Risk of explosion if battery is replaced by an incorrect type. Dispose of used batteries according to the instructions.
Adapter shall be installed near the equipment and shall be easily accessible.
The plug considered as disconnect device of adapter.
The operating temperature of the EUT can't exceed the specified range.

Approved Accessories

- This radio meets the RF exposure guidelines when used with the Reteless accessories supplied or designated for the product. Use of other accessories may not ensure compliance with the RF exposure guidelines and may violate regulations.
For a list of Reteless-approved accessories for your radio model, visit the following website: http://www.Retekess.com

Guarantee

Model Number: _____
Serial Number: _____
Purchasing Date: _____
Dealer: _____ Telephone: _____
User's Name: _____ Telephone: _____
Country: _____ Address: _____
Post Code: _____ Email: _____

- Remarks:
This guarantee card should be kept by the user, no replacement if lost.
Most new products carry a two-year manufacturer's warranty from the date of purchase.
The user can get warranty and after-sales service as below:
Contact the seller where you buy.
Products Repaired by Our Local Repair Center
For warranty service, you will need to provide a receipt proof of purchase from the actual seller for verification
Exclusions from Warranty Coverage:
To any product damaged by accident.
In the event of misuse or abuse of the product or as a result of unauthorized alterations or repairs.
If the serial number has been altered, defaced, or removed.